



DOCUMENTAZIONE

Moonwalk Service

c/o Claudio Giulio Prencipe

Noleggio Audio e Luci | Installazioni per Eventi
via Camogli 11/3 - Rivoli frazione Cascine Vica, 10098 (TO)

+39/3477822465

moonwalkservice@gmail.com

www.noleggio-audio-luci.it | www.moonwalkgroup.com

NB: tutti i diritti appartengono ai rispettivi proprietari;
la presente documentazione viene resa disponibile presso il sito
www.noleggio-audio-luci.it e www.moonwalkgroup.com per
scopi puramente informativi. Vi invitiamo a visitare i siti
dei produttori per consultare le ultime edizioni disponibili.

**J SERIES PROFESSIONAL AMPLIFIER****MODEL: J26A/J36A/J46A**

- Reliable PCB
- Special transformer
- Capacitor with high capacity
- Soft start limiter
- Perfect protection
- Stereo, parallel, bridge mode

Specifications:

Model			J26a	J36a	J46a
Output power TA 1KHz THD≤0.1%	Stereo	8 ohm	260W+260W	360W+360W	400W+400W
		4 ohm	400W+400W	500W+500W	600W+600W
	Bridge	8 ohm	800W	1000W	1200W
Frequency response	10Hz~50KHz -1.5dB				
Input sensitivity	0.77V/26dB/1.4V				
Input impedance	20K ohm				
Signal/noise ratio a-weighted RMS			> 95dB	> 100dB	> 100dB
Crosstalk at rated output power 8 ohm 1KHz			> 70dB	> 70dB	> 70dB
Damping factor f=1KHz 8 ohm			> 200	> 200	> 200
Output circuit type	AB				
Protection	Short circuit, current limited DC fault AC line fuse, thermal cut OFF, power up/down transients, slow start				
Indicators	Power(blue) protect(yellow) clip(red) bridge(green) parallel(green)				
Cooling	Variable speed fan				
Front panel controls	Level ACH, BCH power switch				
Rear panel controls	Stereo/bridge/parallel mode switch, 0.77V/26dB/1.4V input sensitivity switch, ground /lift switch				
Input connectors	Bal XLR , bal1/4"				
Output connectors	Binding posts 2-pole, 4-pole Speakon				
Power consumption half power 8 ohm			< 350W	< 480W	< 540W
Power supply	AC 115V/230V 50~60Hz				
Product/Shipping dimensions(WxDxH)	482x450x88(530x520x188)mm				
N.W/G.W			16.5kg /18.0kg	18kg /21kg	19.5kg /22.5kg

[<<<Previous page](#) [Next page>>>](#)

CLOSE

Manufacturer: WIND FORCE ELECTRONIC MANUFACTURING CO.,LTD

China: No.4 road 2, Caier industrial and business zone, Shiqiao town, Panyu district, Guangzhou, China P.C. 511400

Tel: 86-20-22871781 22871788 Fax: 86-20-22871799 E-mail: audio@biema.com export@biema.com5718 Kenwick St San Antonio Texas 78238 U.S.A. Tel: 001-210-6842600 Fax: 001-210-8556279 E-mail: gc@biema.us